

KEW 2413F/2413R



photo : 2413F



2413R 10/100ms
True RMS **Ø68** **MAX 1000A** **AC A** **DATA HOLD** **PEAK HOLD**
 Resolution Limit **OUT PUT** **Filter** **☀**

- Large transformer jaws of 68mm diameter makes it possible to clamp on all three or four wires (3 phases) together for leakage current measurement
- Frequency filter switch to eliminate the effect of the harmonics
- 2 way analog output terminal
- Minimum resolution 0.1mA



photo : 2413R

	2413F	2413R
AC A (50/60Hz)	200mA/2/20/200/1000A ±1.5%rdg±2dgt(200mA/2/20A) ±2.0%rdg±2dgt(200A/0 - 500A) ±5.5%rdg(501 - 1000A)	200mA/2/20/200/1000A ±2.5%rdg±5dgt(200mA/2/20A) ±3.0%rdg±5dgt(200A/0 - 500A) ±5.5%rdg(501 - 1000A)
AC A (WIDE)	200mA/2/20/200/1000A ±1.0%rdg±2dgt[50/60Hz] ±3.0%rdg±2dgt[40Hz - 1kHz](200mA/2/20A) ±1.5%rdg±2dgt[50/60Hz] ±3.5%rdg±2dgt[40Hz - 1kHz](200A/0 - 500A) ±5%rdg[50/60Hz] ±10%rdg[40Hz - 1kHz](501 - 1000A)	200mA/2/20/200/1000A ±1.8%rdg±5dgt[50/60Hz] ±3.0%rdg±5dgt[40Hz - 1kHz](200mA/2/20A) ±2.0%rdg±5dgt[50/60Hz] ±3.5%rdg±5dgt[40Hz - 1kHz](200A/0 - 500A) ±5.0%rdg[50/60Hz](501 - 1000A)
Conductor size	φ68mm max.	
Frequency response	40Hz - 1kHz	
Effect of external stray magnetic field φ15mm 100A	10mA AC max.	
Output	Waveform:AC200mV against the maximum value of each range (1000A range is 100mV) Recorder:DC200mV against the maximum value of each range (1000A range is 100mV)	
Crest factor	—	3.0 or less
Applicable Standards	IEC 61010-1 CAT III 300V, IEC 61010-2-032	
Power source	6F22(9V) × 1 *Continuous measuring time : Approx. 60 hours	
Dimension	250(L) × 130(W) × 50(D)mm	
Weight	Approx. 570g	Approx. 600g
Accessories	9094(Carrying case), 6F22 × 1, Instruction manual	
Optional Accessories	7073(2WAY Output cord)	

**COSINUS Messtechnik - Ihr Partner für Messlösung
in allen elektrischen und physikalischen Anwendungen**

COSINUS Messtechnik GmbH

Rotwandweg 4

82024 Taufkirchen

Tel.: 089 / 66 55 94 - 0

Fax: 089 / 66 55 94 -30

office@cosinus.de
www.cosinus.de